



The PW400 12 Volt DC to AC Power Inverter provides 400 watts of continuous power, with a peak surge of 800 watts.

This unit has the following features:

- Anodized aluminum case which provides durability & maximum heat dissipation.
- Built-in Cooling Fan
- External, Replaceable 30 Amp spade-type Fuse
- 12 volt Cigarette Lighter + Power Plug
- Overload Indicator
- Power ON/OFF Switch

| Specifications              |               |
|-----------------------------|---------------|
| Continued Power             | 400W          |
| Peak Load Power Rate        | < 800W        |
| Overload Output Power       | 420-480W      |
| No Load Current Draw        | < 0.12A       |
| Input DC Voltage Range      | 10-15.5V      |
| Output Voltage Range        | 117 +/- 10%   |
| Output Frequency Range      | 60 +/- 3Hz    |
| Max Outer Temperature       | < 65 C        |
| Max Power Efficiency        | > 90%         |
| High Voltage Cut Off Level  | 15.5 +/- 1V   |
| Low Voltage Alarm Level     | 10.5 +/- 0.5V |
| Low Voltage Cut Off Level   | 10 +/- 0.5V   |
| Short Protect               | Yes           |
| Overload Protect            | Yes           |
| Dimension (LxWxH) in        | 7.4 x 5 x 2   |
| Weight                      | 5.0 lbs       |
| Standard Test Voltage Input | DC 12V        |